

Advantages

Minimum size at high output

Low height

Dual input voltage for series or parallel connection

Dual output voltage for series or parallel connection

Permanent corrosion protection, high insulation value and maximum electrical reliability thanks to XtraDenseFill resin encapsulation

Self-extinguishing potting material


Applications

As a mains transformer for adjustment of the voltage and simple electrical

As an isolating transformer for the safe electrical isolation of the input and output sides. The transformer may be used to set up protective separation as a protective measure in accordance with VDE 0100.

As a safety isolating transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Sample application



Standards

Approvals







VDE, UL 5085-1/-2, CSA 22.2 No.66





Safety isolating transformer **FL 14/6**

	Туре	FL 14/6		Туре	FL 14/6
Electrical data 🕂	Input		lechanical data	l ype Terminal and mounting Terminals	
	Rated input voltage	2 x 115 Vac		Terminals	Pins for PCB
	Rated frequency	50 - 60 Hz		Measures and weights	
	Output			Core type	UI 39/10,2
	Rated output voltage	2 x 6 Vac		Weight	0.32 kg
	Rated Power	14 VA			
	No-load voltage (app. x factor)	1.28		Ø 0.8 11.5	
	No-load loss (typ.)	1.20 W		5.5	
	Efficiency	74.0 %		16.0	26.0
	Standards				10.0
	Classification	Safety isolating transformer		15.0 PRI SEC	50.0
	Approvals			45.0 62.5 68.0	57.0
	Approvals	cURus, VDE			
	Environment				
	Ambient temperature max.	40 °C			
	Safety and protection				
	Туре	Encapsulated			
	Insulation class	VDE=E, UL=class 105			
	Protection index	IP 00			
	Safety class (prepared)	II			
	Short circuit strength	non-short-circuit proof			
	Order numbers				
	Order Number	FL 14/6			



