LR3A 40-3/90 Discontinued line - not for new designs



Advantages

Use as line reactor, commutating reactor or PFC reactor

Weight reduction through aluminum winding

Ensuring the short-circuit voltage of 3, 4 or 5 % to the mains

Power harmonic damping

Starting current limitation

Increases the service life of consumers

Low ripple

Bridging voltage dips

Peak current limitation

Very good corrosion protection and low noise thanks to vacuum impregnation $% \left(1\right) =\left(1\right) \left(1\right)$

Integrated lifting rings

Applications

Line reactor to minimise mains pollution, to reduce the reactive-power components and charging currents in the DC link capacitor and to improve the cos(phi).

Standards

Line- and commutation reactor to DIN EN 61558-2-20, IEC 61558-2-20, UL 506, CSA 22.2 $\,$

Approvals



UL 506, CSA 22.2





Line reactor, three-phase, aluminium

LR3A 40-3/90 Discontinued line - not for new designs

	Туре	LR3A 40-3/90 Discontinued		Type		LR3A 40-3/90 Discontinued
၊+ ԴԸ		line - not for new designs	30			line - not for new designs
	Operating data	-	ata	Terminal and mounting		-
_	Rated voltage	3 x 400 Vac		Terminals phase		Flat copper
data	Rated voltage (IEC)	3 x 690 Vac		Terminals PE		for M8
Electrical da	Rated voltage (UL)	3 x 600 Vac		Fixing method		Fixing rail
	Short circuit voltage uK	3 % @ 400 Vac		Fixing screws		M8
	Rated frequency range high	50 Hz		Measures and weights		
	Voltage drop	6.9 Vac		Weight		10.64 kg
	Rated current	90 A		vvoigno		10.0 T Ng
	Inductance	0.245 mH				
	Inductance deviation	±10 %		0 0 0		
	Output				177.0	
	Power loss	263.4 W				
	Approvals					
	Approvals	cURus			81.0	
	Environment			210.0	105.0	81.0
	Ambient temperature	-10 °C to +40 °C		0.0	0.0	
	Type of cooling	AN				•
	Safety and protection	and protection				
	Туре	Open type				
	Protection index	IP 00				
	Safety class (prepared)	1				
	Insulation class	IEC=H, UL=class 180				
	Test voltage	4000 Vac				
	Order numbers					
	Order Number	LR3A 40-3/90 Discontinued line - not for new designs				



