

Advantages

Minimum size at high output

Also with dual output voltage for series or parallel connection

Permanent corrosion protection, high insulation value and maximum electrical reliability thanks to XtraDenseFill resin encapsulation

Self-extinguishing potting material


Additional mounting option with tabs on the enclosure

Applications

As a mains transformer for adjustment of the voltage and simple electrical isolation.

As a safety isolating transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and $\ensuremath{\mathsf{PELV}}$ circuits because of the limit on the output voltage.

Sample application



Standards

Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6, UL 5085-1/-2, CSA 22.2 No.66

Approvals







VDE, UL 5085-1/-2, CSA 22.2 No.66





Safety isolating transformer **VCM 50/1/9**

	Туре	VCM 50/1/9		Туре	VCM 50/1/9
Electrical data +9	Input		0	Terminal and mounting	
	Rated input voltage	230 Vac	Θ.	Fixing method	Fixing points on the case
	Rated frequency	50 - 60 Hz		Terminals	Quick connect terminals
	Output		Mechanical data	Measures and weights	
	Rated output voltage	9 Vac	9	Pin (ø)	PRI 4.8 x 0.8 mm,
	Rated Power	50 VA	<u></u>		SEC 6.3 x 0.8 mm
	No-load voltage (app. x factor)	1.09	.ie	Core type	EI 66/34,5
	No-load loss (typ.)	3.80 W	le le	Weight	0.99 kg
	Efficiency	87.0 %	20		
	Standards		ž	15.0	8.3
	Classification	Safety isolating transformer		 	
	Approvals			SEC 35.0 58.5	37.5
	Approvals	cURus, VDE			
	Environment				
	Ambient temperature max.	40 °C		4	82.0
	Safety and protection			35.0	94.0
	Туре	Encapsulated		00.0	
	Insulation class	VDE=B, UL=class 105			
	Protection index	IP 00			
	Safety class (prepared)	II			
	Short circuit strength	non-short-circuit proof			
	Order numbers				
	Order Number	VCM 50/1/9			

