Safety isolating transformer **VC 16/1/18**



Standards

Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6, UL 5085-1/-2, CSA 22.2 No.66

Advantages

Minimum size at high output

Also with dual output voltage for series or parallel connection

Permanent corrosion protection, high insulation value and maximum electrical reliability thanks to XtraDenseFill resin encapsulation

Self-extinguishing potting material

Applications


Approvals

VDE, UL 5085-1/-2, CSA 22.2 No.66

As a mains transformer for adjustment of the voltage and simple electrical isolation.

As a safety transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Sample application







Safety isolating transformer VC 16/1/18

iput ated input voltage	
ated input voltage	
allou input voltage	230 Vac
ated frequency	50 - 60 Hz
utput	
ated output voltage	18 Vac
ated Power	16 VA
o-load voltage (app. x factor)	1.24
o-load loss (typ.)	1.80 W
ficiency	76.0 %
tandards	
assification	Safety isolating transformer
pprovals	
oprovals	cURus, VDE
nvironment	
mbient temperature max.	40 °C
afety and protection	
ре	Encapsulated
sulation class	VDE=B, UL=class 105
rotection index	IP 00
afety class (prepared)	II
nort circuit strength	non-short-circuit proof
rder numbers	
rder Number	VC 16/1/18
	ated frequency utput utput ated output voltage ated Power o-load voltage (app. x factor) o-load loss (typ.) ficiency tandards assification pprovals assification pprovals assification abient temperature max. afety and protection pe sulation class rotection index afety class (prepared) ort circuit strength rder numbers

